

Value+

Cable Length Meters w/ Multimeters

- No Calibration is needed for general measurement
- Allow User Calibration for precise measurement
- Able to measure cable made of different material
- Only need to connect the cable at one side
- Measure up to 300 meters
- Able to measure Lan cable (both 4P4C & 8P8C), Phone wire and BNC cable
- Intelligent wiremap (Shorts and Split Pairs)
- Digital and Analogue signal selectable (WT36C)
- Auto power off
- With display backlight & flashlight
- Sensitivity adjustable
- With Build-in Multimeter Functions



Cable Length Meter w/ Multimeter



		WT36A	WT36B	WT36C	
Cable Length Measurement	2-100m	Resolution Best Accuracy	0.1m $\pm(1\%+0.5m)$		
	2-200m	Resolution Best Accuracy		0.1m $\pm(1\%+0.5m)$	
	201-300m	Resolution Best Accuracy		0.1m $\pm(1\%+0.5m)$	
Intelligent Wiremap	Shorts		✓	✓	
	Split pair		✓	✓	
	Breakpoint checking		✓	✓	
	Length of Network Cable (8P8C)		✓	✓	
	Length of Network Cable (4P4C)		✓	✓	
	Length of Phone Cable		✓	✓	
	Length of BNC Cable		✓	✓	
Analogue Cable Tracing	Digitalized Cable Tracing		✓	✓	
	Remote Identification (Optional)		7	7	
	User Calibratable		✓	✓	
	User Calibration Result Storage		✓	✓	
Multimeter	DC Voltage	400mV/4V/40V/400V	$\pm(0.8\%+5)$	$\pm(0.8\%+5)$	$\pm(0.8\%+5)$
	AC Voltage	4V/40V/400V	$\pm(2.5\%+5)$	$\pm(2.5\%+5)$	$\pm(2.5\%+5)$
	DC Current	10A	$\pm(2.5\%+5)$	$\pm(2.5\%+5)$	$\pm(2.5\%+5)$
	AC Current	10A	$\pm(3.5\%+5)$	$\pm(3.5\%+5)$	$\pm(3.5\%+5)$
	Resistance	400Ω/4kΩ/40kΩ/400kΩ/4MΩ/40MΩ	$\pm(3\%+5)$	$\pm(3\%+5)$	$\pm(3\%+5)$
	Capacitance	40nF/400nF/4μF/40μF/100μF	$\pm(5\%+5)$	$\pm(5\%+5)$	$\pm(5\%+5)$
	Diode		✓	✓	✓
	Continuity		✓	✓	✓
	Max Display		1999	1999	1999
	Display Mode			Vertical Alignment	
Display Backlight		✓	✓	✓	
Flashlight		✓	✓	✓	
Sensitivity adjustable		✓	✓	✓	
Low power indication		✓	✓	✓	
Auto power off		✓	✓	✓	
Power By		3.7V 1800mAH 18650 Li-ion Battery x1			

* All information provided are subject to change without prior notice.

Futronix Co.

HONG KONG

www.futronix-hk.com

info@futronix-hk.com



Your Distributor :